


R&S® FSC

Spectrum Analyzer

Specifications

3 year warranty



CONTENTS

Base unit	3
Frequency	3
Sweep time.....	3
Bandwidths.....	3
Level.....	4
Trigger functions.....	5
Tracking generator (model .13/.16 only)	6
Inputs and outputs	7
General data	8
Ordering information	9
Options.....	9
Recommended extras.....	10
Supported Power Sensors	11

Specifications apply under the following conditions:

15 minutes warm-up time at ambient temperature, specified environmental conditions met, calibration cycle adhered to.

Data without tolerances: typical values only. Data designated as “nominal” applies to design parameters and is not tested.

Base unit

Frequency

Frequency range	model .03/.13	9 kHz to 3 GHz
	model .06/.16	9 kHz to 6 GHz
Frequency resolution		1 Hz

Reference frequency, internal, nominal		
Aging per year		1×10^{-6}
Temperature drift	0 °C to +30 °C	1×10^{-6}
	+30 °C to +50 °C	3×10^{-6}
Achievable initial adjustment accuracy		5×10^{-7}
Total reference uncertainty		(time since last adjustment × aging rate) + temperature drift + calibration accuracy

Frequency readout		
Marker resolution		0.1 Hz
Uncertainty		$\pm(\text{marker frequency} \times \text{reference uncertainty} + 10\% \times \text{resolution bandwidth} + \frac{1}{2}(\text{span}/(\text{sweep points} - 1)) + 1 \text{ Hz})$
Number of sweep (trace) points		631
Marker tuning frequency step size		span/630
Frequency counter resolution		0.1 Hz
Count uncertainty	S/N > 25 dB	$\pm(\text{frequency} \times \text{reference uncertainty} + \frac{1}{2}(\text{last digit}))$
Frequency span		
Span setting uncertainty		$\pm\text{span}/630$

Spectral purity, SSB phase noise	f = 500 MHz, carrier offset	
	30 kHz	< -95 dBc (1 Hz), typ. -105 dBc (1 Hz)
	100 kHz	< -100 dBc (1 Hz), typ. -110 dBc (1 Hz)
	1 MHz	< -120 dBc (1 Hz), typ. -127 dBc (1 Hz)

Sweep time

Sweep time	span = 0 Hz	200 µs to 100 s
	$10 \text{ Hz} \leq \text{span} \leq 600 \text{ MHz}$	20 ms to 1000 s
	span > 600 MHz	20 ms × span/600 MHz to 1000 s
Uncertainty	span = 0 Hz	1 %, nominal
	span ≥ 10 Hz	3 %, nominal

Bandwidths

Resolution bandwidths		
Range	-3 dB bandwidth	10 Hz to 3 MHz in 1/3 sequence
Bandwidth accuracy	$10 \text{ Hz} \leq \text{RBW} \leq 300 \text{ kHz}$	< 5 %, nominal
	RBW > 300 kHz	< 10 %, nominal
Selectivity	60 dB:3 dB	< 5 (Gaussian type filters), nominal
Video filters		
Range	-3 dB bandwidth	10 Hz to 3 MHz in 1/3 sequence

Level

Display range		displayed noise floor to +30 dBm
Maximum rated input level with RF attenuation \geq 10 dB		
DC voltage		50 V
CW RF power		30 dBm (= 1 W)
Peak RF power	< 3 s duration	33 dBm (= 2 W)
Max. pulse voltage		150 V
Max. pulse energy	pulse width 10 μ s	10 mWs
Maximum rated input level with RF attenuation < 10 dB		
DC voltage		50 V
CW RF power		20 dBm (= 100 mW)
Peak RF power	< 3 s duration	23 dBm (= 200 mW)
Max. pulse voltage		50 V
Max. pulse energy	pulse width 10 μ s	1 mWs
Intermodulation		
Third-order intermodulation (TOI), nominal values	intermodulation-free dynamic range, signal level 2×-20 dBm, RF attenuation = 0 dB, without RF preamplifier (R&S®FSC-B22 option) or RF preamplifier = OFF	
	$f_{in} < 300$ MHz	> 54 dBc (TOI > +7 dBm, typ. +11 dBm)
	$300 \text{ MHz} \leq f_{in} < 3.6$ GHz	> 60 dBc (TOI > +10 dBm, typ. +15 dBm)
	$3.6 \text{ GHz} \leq f_{in} \leq 6$ GHz	> 46 dBc (TOI > +3 dBm, typ. +10 dBm)
	signal level 2×-40 dBm, RF attenuation = 0 dB, RF preamplifier (R&S®FSC-B22 option) = ON	
	$f_{in} < 300$ MHz	> 50 dBc (TOI -15 dBm)
	$300 \text{ MHz} \leq f_{in} \leq 6$ GHz	> 56 dBc (TOI -12 dBm)
Second harmonic intercept (SHI), nominal values	RF attenuation = 0 dB, without RF preamplifier (R&S®FSC-B22 option) or RF preamplifier = OFF	
	$f_{in} = 20$ MHz to 1.5 GHz	+40 dBm
	$f_{in} = 1.5$ GHz to 3 GHz	+30 dBm
	RF attenuation 0 dB, RF preamplifier (R&S®FSC-B22 option) = ON	
	$f_{in} = 100$ MHz to 3 GHz	0 dBm
Displayed average noise level	RF attenuation 0 dB, termination 50 Ω , RBW = 100 Hz, VBW = 10 Hz, sample detector, log scaling, tracking generator = OFF, normalized to 1 Hz, without RF preamplifier (R&S®FSC-B22 option) or RF preamplifier = OFF	
	frequency	
	9 kHz to 100 kHz	< -108 dBm, typ. -118 dBm
	100 kHz to 1 MHz	< -115 dBm, typ. -125 dBm
	1 MHz to 10 MHz	< -136 dBm, typ. -144 dBm
	10 MHz to 2 GHz	< -141 dBm, typ. -146 dBm
	2 GHz to 3.6 GHz	< -138 dBm, typ. -143 dBm
	3.6 GHz to 5 GHz	< -142 dBm, typ. -146 dBm
	5 GHz to 6 GHz	< -140 dBm, typ. -144 dBm
	RF attenuation 0 dB, termination 50 Ω , RBW = 100 Hz, VBW = 10 Hz, sample detector, log scaling, tracking generator = OFF, normalized to 1 Hz, RF preamplifier (R&S®FSC-B22 option) = ON	
	frequency	
	100 kHz to 1 MHz	< -133 dBm, typ. -143 dBm
	1 MHz to 10 MHz	< -157 dBm, typ. -161 dBm
	10 MHz to 1 GHz	< -161 dBm, typ. -165 dBm
	1 GHz to 2 GHz	< -159 dBm, typ. -163 dBm
	2 GHz to 5 GHz	< -155 dBm, typ. -159 dBm
	5 GHz to 6 GHz	< -151 dBm, typ. -155 dBm

Immunity to interference, nominal values		
Image frequencies	$f_{in} - 2 \times 21.4$ MHz	< -70 dBc, typ. -80 dBc
	$f_{in} - 2 \times 831.4$ MHz	< -70 dBc, typ. -90 dBc
	$f_{in} - 2 \times 4881$ MHz	-60 dBc
Intermediate frequencies	21.4 MHz, 831.4 MHz, 4881.4 MHz	-60 dBc, typ. -80 dBc
	8931.4 MHz	-50 dBc
Other interfering signals, signal level – RF attenuation < -20 dBm	$f \leq 3.6$ GHz spurious at $f_{in} - 2440.7$ MHz	< -60 dBc
	3.6 GHz < $f \leq 6$ GHz spurious at $f_{in} - 4465.7$ MHz	< -60 dBc
	$f \leq 3.6$ GHz	
Other interfering signals, related to local oscillators	$\Delta f < 300$ kHz	-60 dBc
	$\Delta f \geq 300$ kHz	< -60 dBc
	$f > 3.6$ GHz	
	$\Delta f < 300$ kHz	-54 dBc
	$\Delta f \geq 300$ kHz	< -54 dBc
	$f =$ receive frequency	
Residual spurious response	input matched with 50 Ω , without input signal, RBW ≤ 30 kHz, $f \geq 3$ MHz, RF attenuation = 0 dB, tracking generator = OFF	< -90 dBm

Level display		
Logarithmic level axis		1/2/5/10/20/50/100 dB, 10 divisions
Linear level axis		0 % to 100 %, 10 divisions
Number of traces		2
Trace detectors		max peak, min peak, auto peak, sample, RMS
Trace functions		clear/write, max hold, min hold, average, view
Setting range of reference level		-80 dBm to +30 dBm
Units of level axis		dBm, dBmV, dB μ V, V, W

Level measurement uncertainty		
Absolute level uncertainty at 100 MHz	+20 °C to +30 °C	± 0.3 dB ($\sigma = 0.1$ dB)
Frequency response (+20 °C to +30 °C)	9 kHz $\leq f < 10$ MHz	± 1.5 dB, nominal
	10 MHz $\leq f \leq 3.6$ GHz	± 1 dB ($\sigma = 0.33$ dB)
	3.6 GHz < $f \leq 6$ GHz	± 1.5 dB ($\sigma = 0.5$ dB)
Attenuator uncertainty		± 0.3 dB ($\sigma = 0.1$ dB)
Uncertainty of reference level setting		± 0.1 dB, nominal
Display nonlinearity	S/N > 16 dB, 0 dB to -50 dB, logarithmic level display	± 0.2 dB ($\sigma = 0.067$ dB)
Bandwidth switching uncertainty	reference: RBW = 10 kHz	± 0.1 dB, nominal
Total measurement uncertainty	95 % confidence level, +20 °C to +30 °C, S/N > 16 dB, 0 dB to -50 dB below reference level, RF attenuation auto	
	10 MHz < $f \leq 3.6$ GHz	± 1 dB, typ. ± 0.5 dB
	3.6 GHz < $f \leq 6$ GHz	± 1.5 dB, typ. ± 1 dB

Trigger functions

Trigger		
Trigger source		free run, video, external
External trigger level	low \rightarrow high transition	2.4 V, nominal
	high \rightarrow low transition	0.7 V, nominal

Tracking generator (model .13/.16 only)

Frequency range	model .13	100 kHz to 3 GHz
	model .16	100 kHz to 6 GHz
Connector		N female, 50 Ω
VSWR	$100 \text{ kHz} \leq f \leq 1 \text{ GHz}$	< 1.5, nominal
	$1 \text{ GHz} < f \leq 3 \text{ GHz}$	< 2, nominal
	$3 \text{ GHz} < f \leq 6 \text{ GHz}$ (model .16 only)	< 2, nominal
Output level	tracking generator attenuation = 0 dB	0 dBm, nominal
Tracking generator attenuator		0 dB to 40 dB in 1 dB steps
Dynamic range	RF attenuation = 0 dB, tracking generator attenuation = 10 dB, RBW = 1 kHz	
	$100 \text{ kHz} \leq f < 300 \text{ kHz}$	> 60 dB, typ. 80 dB
	$300 \text{ kHz} \leq f < 3 \text{ GHz}$	> 70 dB, typ. 90 dB
	$3 \text{ GHz} \leq f < 6 \text{ GHz}$ (model .16 only)	> 70 dB, typ. 90 dB
Reverse power		
DC voltage		50 V
CW RF power		+20 dBm (= 0.1 W)
Max. pulse voltage		50 V
Max. pulse energy (10 μ s)		1 mWs

Inputs and outputs

RF input		
Impedance		50 Ω
Connector		N female
VSWR	100 kHz \leq f \leq 1 GHz	< 1.5, nominal
	1 GHz < f \leq 6 GHz	< 2, nominal
Setting range of input attenuator		0 dB to 40 dB in 5 dB steps
RF preamplifier gain	with R&S®FSC-B22 option	20 dB, nominal
AF output		
AF demodulation types		AM and FM
Connector		3.5 mm mini jack
Output impedance		32 Ω , nominal
Voltage (open circuit)		V _{RMS} adjustable from 0 V to > 100 mV
USB interface		
Front panel		USB host interface, version 1.1
Connector		USB type A plug, version 1.1
Memory sticks supported		\leq 4 Gbyte, USB version 1.1 or 2.0
Rear panel		USB device interface, version 1.1
Connector		USB type B plug, version 1.1
External reference, external trigger		
Connector		BNC female, 50 Ω
Mode	selectable	external reference, external trigger
External reference input	required level	0 dBm
	frequency	10 MHz
External trigger threshold	low \rightarrow high transition	2.4 V, nominal
	high \rightarrow low transition	0.7 V, nominal
IF out		
Connector		BNC female, 50 Ω
Frequency		21.4 MHz
DC supply input		
Connector		5 mm DIN 45323 female
Input voltage range		14 V to 16 V, nominal
Input current		0.9 A to 0.7 A

General data

Power supply		
AC supply	input specifications	100 V AC to 240 V AC, 50 Hz to 60 Hz, 400 Hz, 130 VA
DC supply	input specifications	14 V to 16 V, 0.9 A to 0.7 A, nominal
Power consumption		12 W, nominal
Safety		in line with IEC 61010-1, EN 61010-1, CAN/CSA C22.2 No. 61010-1-04, UL61010-1
Test mark		VDE - GS, cCSA _{US} ,

Manual operation		
Languages		Chinese, English, French, German, Italian, Hungarian, Japanese, Korean, Portuguese, Russian, Spanish
Remote control		
Command set		SCPI 1997.0
LAN interface		10/100BaseT, RJ-45
USB interface	rear panel	USB device, type B
Display		
Type		14.5 cm (5,7") LCD TFT color
Resolution		640 x 480 pixel
Audio		
Speaker		internal
Mass memory		
Mass memory		flash memory (internal) USB memory stick (not supplied)
Data storage	internal	> 256 instrument settings and traces
	external, on 1 Gbyte USB memory stick	> 5000 instrument settings and traces
Temperature		
	operating temperature range	+0 °C to +50 °C
	permissible temperature range	+0 °C to +55 °C
	storage temperature range	-40 °C to +70 °C
Climatic loading	relative humidity	+25/+40 °C at 85 % relative humidity (IEC 60068-2-30)
Mechanical resistance		
Vibration	sinusoidal	IEC 60068-2-6
	random	IEC 60068-2-64
Shock		40 g shock spectrum, in line with MIL-STD-810E, method 516.4 procedure 1, IEC 60068-2-27
EMC		
		in line with EMC Directive 2004/108/EC including: IEC/EN 61326-1 ^{1, 2} , IEC/EN 61326-2-1, CISPR 11/EN 55011 ¹ IEC/EN 61000-3-2, IEC/EN 61000-3-3

Weight and dimensions		
Dimensions	W x H x D	233 mm x 158.1 mm x 350 mm (9.2 in x 6.2 in x 13.8 in)
Weight		4.5 kg (9.9 lb)

Recommended calibration interval		
		1 year

¹ RF emission in line with EN 55011 class A, operation in residential, commercial and business areas or in small-size companies is not covered. Thus, the instrument may not be operated in residential, commercial and business areas or in small-size companies, unless additional measures are taken to ensure that EN 55011 class B is complied with.

² Immunity test requirement for industrial environment (EN 61326 table 2).

Ordering information

Designation	Type	Order No.
Spectrum Analyzer, 9 kHz to 3 GHz	R&S®FSC3	1314.3006.03
Spectrum Analyzer, 9 kHz to 3 GHz, with tracking generator	R&S®FSC3	1314.3006.13
Spectrum Analyzer, 9 kHz to 6 GHz	R&S®FSC6	1314.3006.06
Spectrum Analyzer, 9 kHz to 6 GHz, with tracking generator	R&S®FSC6	1314.3006.16
Accessories supplied		
Power cable, USB cable for connection to PC, quick start guide and CD-ROM (with operating manual and service manual)		

Options

Designation	Type	Order No.
Preamplifier, 100 kHz to 3 GHz/6 GHz (for the R&S®FSC3/6)	R&S®FSC-B22	1314.3535.02

Recommended extras

Designation	Type	Order No.
Ethernet Cable	R&S®HA-Z210	1309.6152.00
Headphones	R&S®FSH-Z36	1145.5838.02
19" Rack Adapter for installing two R&S®FSC	R&S®ZZA-T33	1109.4458.00
19" Rack Adapter for installing one R&S®FSC	R&S®ZZA-T34	1109.4464.00
Matching pad 50/75 Ω, 0 Hz to 2700 MHz, matching at both ends, N-connectors	R&S®RAM	0358.5414.02
Matching pad 50/75 Ω, 0 Hz to 2700 MHz, matching at one end, N-connectors	R&S®RAZ	0358.5714.02
75 ohm matching pad N to BNC (female)	R&S®FSH-Z38	1300.7740.02
Near-Field Probe Set	R&S®HZ-15	1147.2736.02
Preamplifier for R&S®HZ-15	R&S®HZ-16	1147.2720.02

Supported Power Sensors ³

Designation	Type	Order No.
Universal Power Sensor, 10 MHz to 8 GHz, 100 mW, 2-path	R&S [®] NRP-Z211	1417.0409.02
Universal Power Sensor, 10 MHz to 18 GHz, 100 mW, 2-path	R&S [®] NRP-Z221	1417.0309.02
R&S[®]NRP-Zxx power sensors require the following adapter cable for operation on the R&S[®]FSC		
USB Adapter Cable (passive), length: 2 m (78.7 in), to connect R&S [®] NRP-Zxx S/SN power sensors to the R&S [®] Spectrum Rider	R&S [®] NRP-Z4	1146.8001.02

Warranty		
Base unit		3 years
All other items ⁴		1 year
Options		
Extended Warranty, one year	R&S [®] WE1	Please contact your local Rohde & Schwarz sales office.
Extended Warranty, two years	R&S [®] WE2	
Extended Warranty with Calibration Coverage, one year	R&S [®] CW1	
Extended Warranty with Calibration Coverage, two years	R&S [®] CW2	

Extended warranty with a term of one and two years (WE1 and WE2)

Repairs carried out during the contract term are free of charge ⁵. Necessary calibration and adjustments carried out during repairs are also covered.

Extended warranty with calibration coverage (CW1 and CW2)

Enhance your extended warranty by adding calibration coverage at a package price. This package ensures that your Rohde & Schwarz product is regularly calibrated, inspected and maintained during the term of the contract. It includes all repairs ⁵ and calibration at the recommended intervals as well as any calibration carried out during repairs or option upgrades.

For product brochure, see PD 5214.3330.32 and at www.rohde-schwarz.com.

³ For average power measurement only.

⁴ For options that are installed, the remaining base unit warranty applies if longer than 1 year. Exception: all batteries have a 1 year warranty.

⁵ Excluding defects caused by incorrect operation or handling and force majeure. Wear-and-tear parts are not included.

Service that adds value

- | Worldwide
- | Local and personalized
- | Customized and flexible
- | Uncompromising quality
- | Long-term dependability

Rohde & Schwarz

The Rohde & Schwarz electronics group offers innovative solutions in the following business fields: test and measurement, broadcast and media, secure communications, cybersecurity, monitoring and network testing. Founded more than 80 years ago, the independent company which is headquartered in Munich, Germany, has an extensive sales and service network with locations in more than 70 countries.

Sustainable product design

- | Environmental compatibility and eco-footprint
- | Energy efficiency and low emissions
- | Longevity and optimized total cost of ownership

Certified Quality Management

ISO 9001

Certified Environmental Management

ISO 14001

Rohde & Schwarz GmbH & Co. KG

www.rohde-schwarz.com

Rohde & Schwarz training

www.training.rohde-schwarz.com

Regional contact

- | Europe, Africa, Middle East | +49 89 4129 12345
customersupport@rohde-schwarz.com
- | North America | 1 888 TEST RSA (1 888 837 87 72)
customer.support@rsa.rohde-schwarz.com
- | Latin America | +1 410 910 79 88
customersupport.la@rohde-schwarz.com
- | Asia Pacific | +65 65 13 04 88
customersupport.asia@rohde-schwarz.com
- | China | +86 800 810 82 28 | +86 400 650 58 96
customersupport.china@rohde-schwarz.com

R&S® is a registered trademark of Rohde & Schwarz GmbH & Co. KG

Trade names are trademarks of the owners

PD 5214.3330.22 | Version 03.00 | February 2017 (as)

R&S®FSC Spectrum Analyzer

Data without tolerance limits is not binding | Subject to change

© 2009 - 2017 Rohde & Schwarz GmbH & Co. KG | 81671 Munich, Germany



5214333022