




DEHNgard® modular DG S WE 600 (FM)

DE Einbuanleitung
GB Installation instructions
IT Istruzioni di montaggio
FR Instructions de montage
NL Montagehandleiding
ES Instrucciones de montaje
PT Instruções de montagem
DK Monteringsvejledning
SE Monteringsanvisning
FI Asennusohje
GR Οδηγίες συναρμολόγησης
PL Instrukcja montażu
CZ Montážní návod
TR Kurulum Talimatları
RU Инструкция по монтажу
CN 安装说明
HU Szerelési útmutató
JP 設置説明書





II IEC 61643-11...
 2 EN 61643-11...

Pozidriv®Z2 4 Nm




DG S WE 600 (FM)

	DG MOD 750
U_N	480 V (50/60 Hz) Tol.: 0V ... U_C
U_C	600 V (50/60 Hz)
U_{mov}	750 V (50/60 Hz)
max.	100 A gG
$I_{max.}$	25 kA
I_{SCCR}	25 k Arms
θ°	-40°C ... +80°C
φ	5% ... 95%
I_{PE}	< 0,3 mA
IP 1	20
L x W x H	90 mm x 18 mm x 73 mm

min. □ L, N, $\frac{1}{\sqrt{3}}$	12 mm	12 mm	12 mm
max. □ L, N, $\frac{1}{\sqrt{3}}$	1,5 mm ²	25 mm ²	35 mm ²
□	16 mm ² Cu	$\geq 15,5$ mm	

TNC

DEHNgard®modular
DG S WE 600 (FM)

DEHNgard®modular
DG S WE 600 (FM)

F1 A gG	S ₂ / mm ²	S ₃ / mm ²	S ₄ / mm ²	F2 A gG
25	4	6	6	---
35	4	6	6	---
40	4	6	6	---
50	6	6	6	---
63	10	10	10	---
80	10	10	10	---
100	16	16	16	---
>100	16	16	16	100

LPZ 0_A

DEHNgard®modular
DG S WE 600 (FM)

U_N / I_N	AC: 250 V / 0,5 A
DC:	250 V / 0,1 A 125 V / 0,2 A 75 V / 0,5 A
	(0,2 Nm)
	max. 1,5 mm ²

